

Date		Project	
Type		Part Number	

EMERGENCY Series

Internal Mount Emergency Driver

The RENO-EM-C08 meets Standard CSA C22.2 NO.141, UL924 and has the following features: Over Charge protection, Over Discharge protection, and Short Circuit Protection. When the AC power goes out, the emergency driver detects the AC power outage and automatically switches to emergency mode - The red LED light switches off. When the AC power is restored, the emergency driver returns to AC mode and begins recharging - The red LED light switches on.



PRODUCT FEATURES

- UL listed for factory and field installation Standard of CSA C22.2 NO.141, UL9240
- CEC Title 20 Compliant
- Constant power output
- Battery protections: over charge, over discharge, short circuit protection
- Compatible with a wide variety of LED fixtures and AC drivers
- Operating Temperature: 35°C to +60°C (41°F to 140°F)
- 5 year warranty

KEY SPECIFICATIONS

Input Voltage	100-347V 50/60Hz
Input Current	100mA
Input Power	7W Max
Output Voltage	Up to 56Vdc
Output Power	8W
Recharge Time	24 Hours
Discharge Time	90 Minutes
Charging Current	≤250mA
Applications	Commercial, Warehouse, Retail Facilities

SPECIFICATIONS

Order#	Model	Wattage	Input Voltage	Discharge Time	Recharge Time	Battery Type
R83004	RENO-EM-C08	8W	100-347V	90 Minutes	24hrs	LiFeP04 Battery

DIMENSIONS

